

10/019,888
2 of 26**AMENDMENTS TO THE CLAIMS**

This listing of claims will replace all prior versions, and listings, of claims in the application:

Complete Listing of Claims:

Claims 1-32 (Previously Cancelled).

33. (Previously Added) The boost bridge amplifier comprising:
a power supply (1), having a first and a second nodes,
a mono- or poly-phase load (5), having a first and a second nodes per each phase,
a switching bridge (3), having a first and a second nodes, common for all phases, and
an output node per each phase,
a bridge capacitor (6), having a first and a second nodes,
characterized in that,
the first node of said power supply (1) is connected to the first node of each phase of
said load (5),
the second node of said power supply (1) is connected to the second node of said
switching bridge (3) and the second node of said bridge capacitor (6),
the first node of said bridge capacitor (6) is connected to the first node of said
switching bridge (3), and
the second node of each phase of said load (5) is connected to the output node of the
appropriate phase of said switching bridge (3).

34. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 33,
wherein

the second node of a first phase (51) of said load (5) is connected to the third node of
said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first
and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3),
and the first diode (71) cathode is connected to the first node of said switching bridge (3),

10/019,888

3 of 26

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3), and

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3).

35. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 34, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

36. (Previously Added) The boost bridge amplifier of claim 35, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

37. (Previously Added) The boost bridge amplifier of claim 34, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

38. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 33, wherein

the first node of said power supply (1) is connected to the first node of the first phase (51) of said load (5) and the first node of the second phase (52) of said load (5),

the second node of said power supply (1) is connected to the second node of said switching bridge (3) and the second node of said bridge capacitor (6),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of the first phase (51) of said load (5) is connected to the third node of said switching bridge (3),

10/019,888

4 of 26

the second node of the second phase (52) of said load (5) is connected to the fourth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3), and

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3).

39. (Previously Added) The boost bridge amplifier of claim 38, wherein load (5) is a dual voice coil loudspeaker.

40. (Currently Amended) The ~~two~~-phase boost bridge amplifier of claim 38, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5) and the first node of the second phase (52) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

10/019,888

5 of 26

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

41. (Currently Amended) The ~~two~~-phase boost bridge amplifier of claim 40, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

42. (Previously Added) The boost bridge amplifier of claim 40, wherein load (5) is a dual voice coil loudspeaker.

43. (Previously Added) The boost bridge amplifier of claim 40, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

44. (Currently Amended) The ~~two~~-phase boost bridge amplifier of claim 38, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

45. (Previously Added) The boost bridge amplifier of claim 38, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

46. (Currently Amended) The ~~three~~-phase boost bridge amplifier of claim 33, wherein

10/019,888

6 of 26

the first node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), and the first node of the third phase (53) of said load (5),

the second node of said power supply (1) is connected to the second node of said switching bridge (3) and the second node of said bridge capacitor (6),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of the first phase (51) of said load (5) is connected to the third node of said switching bridge (3),

the second node of the second phase (52) of said load (5) is connected to the fourth node of said switching bridge (3),

the second node of the third phase (53) of said load (5) is connected to the fifth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3),

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3),

10/019,888

7 of 26

the fifth active switch (35) of said switching bridge (3) is connected between the first and fifth nodes of said switching bridge (3),

the fifth diode (75) anode is connected to the fifth node of said switching bridge (3), and the fifth diode (75) cathode is connected to the first node of said switching bridge (3),

the sixth active switch (36) of said switching bridge (3) is connected between the fifth and second nodes of said switching bridge (3), and

the sixth diode (76) anode is connected to the second node of said switching bridge (3), and the sixth diode (76) cathode is connected to the fifth node of said switching bridge (3).

47. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 46, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), and the first node of the third phase (53) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

48. (Previously Added) The boost bridge amplifier of claim 47, wherein load (5) is a three-phase electric motor.

49. (Previously Added) The boost bridge amplifier of claim 47, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

50. (Previously Added) The boost bridge amplifier of claim 46, wherein load (5) is a three-phase electric motor.

51. (Previously Added) The boost bridge amplifier of claim 46, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

10/019,888
8 of 26

52. (Previously Added) The boost bridge amplifier of claim 33, wherein load (5) is a dual voice coil loudspeaker.

53. (Previously Added) The boost bridge amplifier of claim 33, wherein load (5) is a three-phase electric motor.

54. (Previously Added) The boost bridge amplifier comprising:
a power supply (1), having a first and a second nodes,
a mono- or poly-phase load (5), having a first and a second nodes per each phase,
an output filter (4), having a first and a second nodes per each phase,
a switching bridge (3), having a first and a second nodes, common for all phases, and
an output node per each phase,
a bridge capacitor (6), having a first and a second nodes,
characterized in that,
the first node of said power supply (1) is connected to the first node of each phase of said load (5),
the second node of said power supply (1) is connected to the second node of said switching bridge (3) and the second node of said bridge capacitor (6),
the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),
the second node of each phase of said load (5) is connected to the first node of the appropriate phase of said output filter (4), and
the second node of each phase of said output filter (4) is connected to the output node of the appropriate phase of said switching bridge (3).

55. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 54, wherein

the second node of a first phase (51) of said load (5) is connected to the first node of first filtering inductor (41),

the second node of first filtering inductor (41) is connected to the third node of said switching bridge (3),

10/019,888

9 of 26

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3), and

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3).

56. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 55, wherein

the first node of the first filtering inductor (41) is connected to the first node of a first filtering capacitor (81), and

the second node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81).

57. (Previously Added) The boost bridge amplifier of claim 56, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

58. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 55, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

59. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 58, wherein

10/019,888

10 of 26

the first node of the first filtering inductor (41) is connected to the first node of the first filtering capacitor (81), and

the first node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81).

60. (Previously Added) The boost bridge amplifier of claim 59, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

61. (Previously Added) The boost bridge amplifier of claim 58, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

62. (Previously Added) The boost bridge amplifier of claim 55, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

63. (Currently Amended) The two-phase boost bridge amplifier of claim 54, wherein

the first node of said power supply (1) is connected to the first node of first phase (51) of said load (5) and the first node of the second phase (52) of said load (5),

the second node of said power supply (1) is connected to the second node of said switching bridge (3) and the second node of said bridge capacitor (6),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of first phase (51) of said load (5) is connected to the first node of the first filtering inductor (41),

the second node of the first filtering inductor (41) is connected to the third node of said switching bridge (3),

the second node of the second phase (52) of said load (5) is connected to the first node of the second filtering inductor (42),

the second node of the second filtering inductor (42) is connected to the fourth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

10/019,888

11 of 26

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3), and

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3).

64. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 63, wherein

the first node of the first filtering inductor (41) is connected to the first node of the first filtering capacitor (81),

the second node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81),

the first node of the second filtering inductor (42) is connected to the first node of the second filtering capacitor (82), and

the second node of said bridge capacitor (6) is connected to the second node of the second filtering capacitor (82).

65. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 64, wherein

10/019,888
12 of 26

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

66. (Previously Added) The boost bridge amplifier of claim 64, wherein load (5) is a dual voice coil loudspeaker.

67. (Previously Added) The boost bridge amplifier of claim 64, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

68. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 63, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5) and the first node of the second phase (52) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

69. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 68, wherein

the first node of the first filtering inductor (41) is connected to the first node of the first filtering capacitor (81),

the first node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81),

the first node of the second filtering inductor (42) is connected to the first node of the second filtering capacitor (82), and

the first node of said bridge capacitor (6) is connected to the second node of the second filtering capacitor (82).

10/019,888
13 of 26

70. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 69, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

71. (Previously Added) The boost bridge amplifier of claim 69, wherein load (5) is a dual voice coil loudspeaker.

72. (Previously Added) The boost bridge amplifier of claim 69, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

73. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 68, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

74. (Previously Added) The boost bridge amplifier of claim 68, wherein load (5) is a dual voice coil loudspeaker.

75. (Previously Added) The boost bridge amplifier of claim 68, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

10/019,888

14 of 26

76. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 63, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

77. (Previously Added) The boost bridge amplifier of claim 63, wherein load (5) is a dual voice coil loudspeaker.

78. (Previously Added) The boost bridge amplifier of claim 63, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

79. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 54, wherein

the first node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), and the first node of the third phase (53) of said load (5),

the second node of said power supply (1) is connected to the second node of said switching bridge (3) and the second node of said bridge capacitor (6),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of the first phase (51) of said load (5) is connected to the first node of the first filtering inductor (41),

the second node of the first filtering inductor (41) is connected to the third node of said switching bridge (3),

the second node of the second phase (52) of said load (5) is connected to the first node of the second filtering inductor (42),

the second node of the second filtering inductor (42) is connected to the fourth node of said switching bridge (3),

10/019,888

15 of 26

the second node of the third phase (53) of said load (5) is connected to the first node of the third filtering inductor (43),

the second node of the third filtering inductor (43) is connected to the fifth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3),

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3),

the fifth active switch (35) of said switching bridge (3) is connected between the first and fifth nodes of said switching bridge (3),

the fifth diode (75) anode is connected to the fifth node of said switching bridge (3), and the fifth diode (75) cathode is connected to the first node of said switching bridge (3),

the sixth active switch (36) of said switching bridge (3) is connected between the fifth and second nodes of said switching bridge (3), and

the sixth diode (76) anode is connected to the second node of said switching bridge (3), and the sixth diode (76) cathode is connected to the fifth node of said switching bridge (3).

10/019,888

16 of 26

80. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 79, wherein

the first node of the first filtering inductor (41) is connected to the first node of the first filtering capacitor (81),

the second node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81),

the first node of the second filtering inductor (42) is connected to the first node of the second filtering capacitor (82),

the second node of said bridge capacitor (6) is connected to the second node of the second filtering capacitor (82),

the first node of the third filtering inductor (43) is connected to the first node of the third filtering capacitor (83), and

the second node of said bridge capacitor (6) is connected to the second node of the third filtering capacitor (83).

81. (Previously Added) The boost bridge amplifier of claim 80, wherein load (5) is a three-phase electric motor.

82. (Previously Added) The boost bridge amplifier of claim 80, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

83. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 79, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), and the first node of the third phase (53) of said load (5),

the first node of said power supply (1) is connected to the first node of said switching bridge (3) and the first node of said bridge capacitor (6), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

10/019,888

17 of 26

84. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 83, wherein

the first node of the first filtering inductor (41) is connected to the first node of the first filtering capacitor (81),

the first node of said bridge capacitor (6) is connected to the second node of the first filtering capacitor (81),

the first node of the second filtering inductor (42) is connected to the first node of the second filtering capacitor (82),

the first node of said bridge capacitor (6) is connected to the second node of the second filtering capacitor (82),

the first node of the third filtering inductor (43) is connected to the first node of the third filtering capacitor (83), and

the first node of said bridge capacitor (6) is connected to the second node of the third filtering capacitor (83).

85. (Previously Added) The boost bridge amplifier of claim 84, wherein load (5) is a three-phase electric motor.

86. (Previously Added) The boost bridge amplifier of claim 84, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

87. (Previously Added) The boost bridge amplifier of claim 83, wherein load (5) is a three-phase electric motor.

88. (Previously Added) The boost bridge amplifier of claim 83, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

89. (Previously Added) The boost bridge amplifier of claim 79, wherein load (5) is a three-phase electric motor.

90. (Previously Added) The boost bridge amplifier of claim 79, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

10/019,888
18 of 26

91. (Previously Added) The boost bridge amplifier of claim 54, wherein load (5) is a dual voice coil loudspeaker.

92. (Previously Added) The boost bridge amplifier of claim 54, wherein load (5) is a three-phase electric motor.

93. (Previously Added) The boost bridge amplifier comprising:
a power supply (1), having a first and a second nodes,
a mono- or poly-phase load (5), having a first and a second nodes per each phase,
a switching bridge (3), having a first and a second nodes, common for all phases, and
an output node per each phase,
a bridge capacitor (6), having a first and a second nodes,
characterized in that,
the first node of said power supply (1) is connected to the first node of each phase of said load (5) and the second node of said bridge capacitor (6),
the second node of said power supply (1) is connected to the second node of said switching bridge (3),
the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3), and
the second node of each phase of said load (5) is connected to the output node of the appropriate phase of said switching bridge (3).

94. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 93, wherein

the second node of a first phase (51) of said load (5) is connected to the third node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

10/019,888

19 of 26

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3), and

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3).

95. (Currently Amended) The ~~mono-phase~~ boost bridge amplifier of claim 94, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5) and the first node of said bridge capacitor (6),

the first node of said power supply (1) is connected to the first node of said switching bridge (3), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

96. (Previously Added) The boost bridge amplifier of claim 95, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

97. (Previously Added) The boost bridge amplifier of claim 94, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

98. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 93, wherein

the first node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5) and the second node of said bridge capacitor (6),

the second node of said power supply (1) is connected to the second node of said switching bridge (3),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of the first phase (51) of said load (5) is connected to the third node of said switching bridge (3),

10/019,888

20 of 26

the second node of the second phase (52) of said load (5) is connected to the fourth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3), and

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3).

99. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 98, wherein

the second node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5) and the first node of said bridge capacitor (6),

the first node of said power supply (1) is connected to the first node of said switching bridge (3), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

10/019,888
21 of 26

100. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 99, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

101. (Previously Added) The boost bridge amplifier of claim 99, wherein load (5) is a dual voice coil loudspeaker.

102. (Previously Amended) The boost bridge amplifier of claim 99, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

103. (Currently Amended) The ~~two-phase~~ boost bridge amplifier of claim 98, wherein

the third node of said switching bridge (3) is connected to the first node of the filtering capacitor (91),

the second node of said filtering capacitor (91) is connected to the first node of an additional load (92), and

the second node of said additional load (92) is connected to the fourth node of said switching bridge (3).

104. (Previously Added) The boost bridge amplifier of claim 98, wherein load (5) is a dual voice coil loudspeaker.

105. (Previously Added) The boost bridge amplifier of claim 98, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

10/019,888
22 of 26

106. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 93, wherein

the first node of said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), the first node of the third phase (53) of said load (5), and the second node of said bridge capacitor (6),

the second node of said power supply (1) is connected to the second node of said switching bridge (3),

the first node of said bridge capacitor (6) is connected to the first node of said switching bridge (3),

the second node of the first phase (51) of said load (5) is connected to the third node of said switching bridge (3),

the second node of the second phase (52) of said load (5) is connected to the fourth node of said switching bridge (3),

the second node of the third phase (53) of said load (5) is connected to the fifth node of said switching bridge (3),

the first active switch (31) of said switching bridge (3) is connected between the first and third nodes of said switching bridge (3),

the first diode (71) anode is connected to the third node of said switching bridge (3), and the first diode (71) cathode is connected to the first node of said switching bridge (3),

the second active switch (32) of said switching bridge (3) is connected between the third and second nodes of said switching bridge (3),

the second diode (72) anode is connected to the second node of said switching bridge (3), and the second diode (72) cathode is connected to the third node of said switching bridge (3),

the third active switch (33) of said switching bridge (3) is connected between the first and fourth nodes of said switching bridge (3),

the third diode (73) anode is connected to the fourth node of said switching bridge (3), and the third diode (73) cathode is connected to the first node of said switching bridge (3),

the fourth active switch (34) of said switching bridge (3) is connected between the fourth and second nodes of said switching bridge (3),

10/019,888
23 of 26

the fourth diode (74) anode is connected to the second node of said switching bridge (3), and the fourth diode (74) cathode is connected to the fourth node of said switching bridge (3),

the fifth active switch (35) of said switching bridge (3) is connected between the first and fifth nodes of said switching bridge (3),

the fifth diode (75) anode is connected to the fifth node of said switching bridge (3), and the fifth diode (75) cathode is connected to the first node of said switching bridge (3),

the sixth active switch (36) of said switching bridge (3) is connected between the fifth and second nodes of said switching bridge (3), and

the sixth diode (76) anode is connected to the second node of said switching bridge (3), and the sixth diode (76) cathode is connected to the fifth node of said switching bridge (3).

107. (Currently Amended) The ~~three-phase~~ boost bridge amplifier of claim 106, wherein

the second node of the said power supply (1) is connected to the first node of the first phase (51) of said load (5), the first node of the second phase (52) of said load (5), the first node of the third phase (53) of said load (5) and the first node of said bridge capacitor (6),

the first node of the said power supply (1) is connected to the first node of said switching bridge (3), and

the second node of said bridge capacitor (6) is connected to the second node of said switching bridge (3).

108. (Previously Added) The boost bridge amplifier of claim 107, wherein load (5) is a three-phase electric motor.

109. (Previously Added) The boost bridge amplifier of claim 107, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

110. (Previously Added) The boost bridge amplifier of claim 106, wherein load (5) is a three-phase electric motor.

10/019,888

24 of 26

111. (Previously Added) The boost bridge amplifier of claim 106, wherein all active switches are semiconductor switches, such as mosfets, IGBT, bipolar transistors or MCT.

112. (Previously Added) The boost bridge amplifier of claim 93, wherein load (5) is a dual voice coil loudspeaker.

113. (Previously Added) The boost bridge amplifier of claim 93, wherein load (5) is a three-phase electric motor.